



YLI ELECTRONIC




Facial Recognition Access Control

Model: YK-1368


Specification

- Working temperature: -25°C~65°C
- Dimension: 105x210x31(mm)
- Installation : Surface mounted
- Standby current: About 220mA
- Minimal illumination : 0.1Lux
- Current of Recognition mode : About 322mA
- Working power: 12W(12V,1A)
- Unlocking current: About 345mA

Installation



Wiring diagram:



Advisement height from ground 150cm ~ 165cm

View Angle:Vertical60°,horizontal 10°

Features

- 1.Capacity : 300 faces and 300 codes
- 2.Default admin code is 1234 , the length of master code & user code 2-6 digits.
- 3.Language : Chinese, English
- 4.System Remind sound : Short“di”sound is 100ms , Long“di”sound is 1s,Incorrect sound is four times short “di” sound.
5. How to open the door ?
Open the door by face
When the visitor stand in front of the outdoor unit, the cameras will show it on screen and compare with storage face photo. Once approved, the screen will says”open the door !”, a long “di” sound will be heard at the same time.
Open the door by user code
When input the user code, the system will check it directly, once approved, the screen will shows”open the door!”, a long “di” sound will be heard at the same time.

Attention


1. If forgot the password, shut off the power and keep pressing “#” , turn on the power, till you see “systems security setting” then release “#”. Then the default admin code back as 1234.
2. Please attention visitor’s face should occupy full screen at least 20% . 50 cm between face to door unit.
3. At standby mode, Lunix system needs 3s to wake up, and 3s more to recognize face, normally needs 6s totally.
4. There’re 50 key points totally, it will recognize success once 40 key points approved. Key points of face features contain ophryon, eyebrow tail, top of the ear, apex nasi, cheekbones, philtrum, angulus oris.
5. Strong self-learning ability, more identification, faster recognition for a same face. ※ Important, Do not install it under back light or strong light area.

Menu Operation

- 1.At standby mode, press “*” to enter Manager Confirm interface.



Input admin password , default 1234.




2. Menu settings.

User setting, Security setting, General setting, Advance setting, time setting, systems information

Note:

In Menu list, press”8” to page down, press”2”to page up, press”*”to confirm, Press”#” to cancel current setting and return to previous menu. It will exit settings if no operation within 30s.



Menu 1, User setting

Item 1 "ID", Press "*", input 1~300 number, press "*" to confirm.

User setting

1. ID

2. Password Unset

3. Face set

4. Delete

Item 2 "Password", Press "*", popup "Reg Password", input 2~6 digits password twice. Then press "*" to confirm.

User setting

1. ID

2.


3. Input

Confirm


Enroll OK!

Esc-# Con-*

Item 3 "Face", Press "*", keep your eyes focus on green frame area and don't move your face, it will recognize face success till the yellow bar filled in at downside. Then it will return to menu setting automatically, press "*" to standby mode. When a registered face close to camera about 30cm~50cm, camera will identify quickly, once success will show user ID and original photo on screen, and release door at the same time.



Face Identify



ID 1

Open the door!

Item 4 "Delete", to delete current position "password" and "face".

Press "*" to delete success.

Delete

Confirm Deletion

No-# Yes-*

Delete

Working!

No-# Yes-*

Menu2, Security setting

Security setting

1. Set Admin Password
2. Set Unlock Time

Item1, Admin password setting

Set Admin Password

Original password

New password

Confirm password

Esc-# Con-*

Item2, Unlock delay setting

Set Unlock Time

Unlock Time :

Please enter 1 ~ 99

Esc-# Con-*

Item3, General setting

General Setting

1. Machine No.
2. Language
3. Date Format
4. Screen Saver

Item4, Advance setting

Advance Setting

1. Delete All Log
2. Delete All Register
3. Default Setting

Item5, System time

Current Time

- :

: :

MON

Esc-# Con-*

Item6, device information

System Information

1. Register Data
2. Product Information

Register

1. User Reg 000/300
2. Frce 000/300
3. Password 000/300

Product Information

1. Product Name
2. Release Time
3. Serial Number
4. Firmware Version

Item7, Device test (for factory testing only)

Device Test

1. Face Test
2. Deviation Test
3. Wake Test
4. Calibration