

SPECIFICATION SHEET HO-02



Wired emergency button. The HO02 button is an accessory for hybrid alarm panels. This button is a panic or emergency button which when pressed releases the alarm or activates it and when you stop pressing it it deactivates to prevent the prevention of some type of theft.

It has an extremely simple operation and easy installation, practical and can be within the decoration environment of your home, it has

stable performance and high durability. Likewise, you can use this button with a normally open (NO) and normally closed (NC) connection.

Features:

- ABS plastic body.
- Contact Mode: COM, NO NC.

Specs:

- Voltage (VDC): ≤ 24
- Operating current: ≤ 300 mA
- Contact mode: NO and NC
- Measurements: 75mm x 20mm x 7mm

INSTALLATION MANUAL HO-02

1. Find the proper location to mount and fix the button.
2. Use 2X22 non-polarized 2-wire cable for alarm.
3. Connect the 2 wires from the button to the determined zone and common terminal inside the Alarm Panel.
4. Connect the 2 wires of the cable to the back of the emergency button to the common and NC or NO terminals.
5. Check that the two wires are perfectly connected to the screws on the emergency button.
6. Connect the resistance required for the compatibility of the alarm panel and the correct operation. NC in series, NO in parallel.
7. Screw the button into the mounting location.

Diagram:

