

Products ▾

Assemble kit

Tech specs

Relay Jeweller

Wireless dry contact relay

Relay Jeweller

More ▾



Device compatibility

Check

Power supply

External power supply

7–24 V \equiv

The relay does not supply additional power to devices connected to it.

Energy consumption

up to 1 W

In standby mode.

Cross-sectional area of the cable

0.75–1.5 mm² (22–14 AWG)

Maximum resistive load

up to 5 A at 24 V \equiv

up to 13 A at 110–230 V \sim

Maximum inductive/capacitive load

up to 3 A at 24 V \equiv

up to 8 A at 110–230 V \sim

Voltage protection

minimum — 6.5 V \equiv

maximum — 36.5 V \equiv

Once the supply voltage exceeds the specified levels, the relay turns off automatically.

Temperature protection

over +65 °C at the installation site

over +85 °C inside the relay

Communication

Jeweller communication technology

Proprietary wireless communication technology to transmit commands, alarms, and events.

Key features:

- Two-way communication.
- Advanced anti-sabotage.
- Block encryption featuring a dynamic key.
- Instant notifications.
- Remote control and configuration in Ajax apps.

[Learn more](#) >

Frequency bands

866.0–866.5 MHz

868.0–868.6 MHz

868.7–869.2 MHz

905.0–926.5 MHz

915.85–926.5 MHz

921.0–922.0 MHz

Depends on the sales region.

Maximum effective radiated power (ERP)

up to 25 mW

Radio signal modulation

GFSK

Radio communication range

up to 1,000 m

Between the relay and a hub (or a range extender) in an open space.

Calculate radio communication range at the facility >

Encrypted communication

All stored and transmitted data are protected by block encryption featuring a dynamic key.

Frequency hopping

To prevent radio interference and jamming.

Learn more >

Key features

Control via smartphone

The user can set up the relay configurations and receive notifications in an Ajax app.

Automation scenarios

- By arming/disarming
- By schedule
- By alarm
- By temperature
- By humidity¹
- By CO₂ concentration¹
- By touching LightSwitch / pressing Button

Learn more >

¹Scenarios by humidity and CO₂ concentrations are available when [LifeQuality Jeweller](#) is added to the system.

Adjustable pulse duration

from 0.5 to 255 s

Operation modes

- pulse
- bistable

Contact state

- normally open
- normally closed

Recommendations

Suitable for indoor or outdoor use when installed in a hermetically sealed enclosure. It is recommended to mount Relay Jeweller on a DIN rail using DIN Holder, which is sold separately.

Buy DIN Holder >

Sabotage protection

Protection against spoofing

device authentication

Communication loss detection

after 36 s

Detection time depends on the Jeweller or Jeweller/Fibra settings.

Learn more >

Enclosure

Dimensions

39 × 33 × 18 mm

Weight

25 g

Operating temperature range

from -10 °C to +64 °C

Operating humidity

up to 75%

Protection class

IP20



Colors

Black



Complete set

Relay Jeweller

Double-sided adhesive tape

Quick start guide

Certification and compliance with standards



Relay Jeweller



Additional information

[Compliance with standards](#)

[User manual](#)

[Learn more >](#)

[Learn more >](#)

Warranty

24 months

[Learn more >](#)


Subscribe


Subscribe to our emails about secure life. No spam.

Subscribe

Request extra help

- ✉ support@ajax.systems
- 📍 @AjaxSystemsSupport_Bot
- 💬 Send a request





Rating 4.8

4,000,000

people worldwide under Ajax protection

🔗 Suggest a feature



Products

Software

Intrusion protection

Video surveillance

Fire and life safety

Comfort and automation

All products

Services

System integrations

Ajax Ready products

Fibra wired protocol

Ajax radio protocols

Solutions

Customer stories

Solutions by facility type

Commercial fire detection and alarm system

Wireless Grade 3 solution

Upgrades and retrofits

How it works

Company

Blog

About us

Press page

Events

For users

Ajax PRO: Tool for Engineers


Ajax Desktop

Ajax PRO Desktop

Ajax Translator PRO

Ajax Cloud Signaling

Scenarios



Support

Manuals and articles

Compliance with standards

Tools

Ajax device compatibility

Video storage calculator

Video device calculator

Battery life calculator

Radio communication range calculator

Switches and outlets configurator

Fibra power supply calculator

All web tools

Monitoring solutions and integrations

Intrusion alarm monitoring

Video monitoring and visual alarm verification

Audio alarm verification

For partners

For partners

Ajax Academy

Partner Portal

[Career](#)

[Ajax Next](#)

[Students at CES 2026](#)

[Reviews and feedback](#)

 [México](#) [Privacy policy](#) [Report a vulnerability](#) [GDPR White Paper](#) [NDAA Statement](#) [Cookie policy](#) [Anti-Spam Policy](#)

[End user agreement](#) [Warranty](#)

© 2025 AJAX SYSTEMS CH. All rights reserved