

KL-2 V2 REMOTE CONTROL

Two-channel wireless remote control corresponding to two relay outputs, designed to control the on/off state of an electric fence energizer, interface card, neighborhood alarm, or any other system.

This model has the following features:

- Capacity to program up to 23 buttons per output.
- Siren tone for event confirmation.
- Memory clearing function to erase programmed buttons on the key fob.
- Other brands of key fobs with 433 MHz buttons can be linked.
- Panic button programming
- Selection of pulse mode or fixed mode on the outputs.
- Button programming confirmation.

Technical Specifications:

- Frequency: 433 MHz.
- Input voltage: 12 Vdc
- Power consumption: 115 mA
- Range of 80m at line of sight.
- Range of 40m between walls.
- Terminals for connecting a 30W siren
- Output relay capacity: 10 Amp. 250 Vac.
- Receiver dimensions: 7.6 x 5.5 x 3 cm.
- Key fob transmitter dimensions:
3.5 x 6 x 1 cm

